

Senseair Sunlight

R32 & R454 A/B/C



A new generation NDIR sensors with Optical Solid-State design

Electronics with no moving parts makes Senseair Sunlight R32 & 454 A/B/C robust and resistant to vibrations.

Any application with a tough environment or in environments with explosion risk is benefited by the solid-state design. It is also the first NDIR sensor with LED technology that truly saves power while maintaining a high precision.

Senseair Sunlight R32 & 454 A/B/C is designed for high volume production with full traceability by sensor serial number on all manufacturing processes and key components.

Every sensor is individually calibrated and is provided with UART (Modbus) and I²C interface. With the ABC function activated, the sensor is maintenance-free.

Senseair Sunlight R32 & 454 A/B/C is a module that is designed for simple integration into products. Senseair Sunlight R32 & 454 A/B/C can be used in a wide range of refrigerant applications based on R32.

Key benefits

- Complies with IEC 60079-29-1
- Complies with sensor element part at IEC and UL 60335-2-40
- Miniature size
- Fast response time
- Maintenance-free
- Long term stability
- Long lifetime
- Immunity to poisoning
- Individually calibrated
- Very low power consumption
- Mass production

Standard specification

Article number	009-4-0001 (R32)
Operating principle	Non-dispersive infrared
Measured gas	R32, R454A, R454B, R454C ¹
Measurement range	0–50 LFL
Accuracy (R32)	±2.5 LFL
Operating conditions	–40–70 °C 0–95% RH
Warm-up time	0s
Response time $\tau_{63\%}$	< 12s
Power supply	3.05–5.5V
Peak current	< 95mA
Average current	1–94µA
Communication	UART, I ² C
Outputs	Digital
Compliance	IEC 60079-29-1 IEC/UL 60335-2-40 (sensor element part)
Maintenance	Periodic Zero calibration or ABC calibration
Life expectancy	> 15 years
Dimensions	34x21x12mm
Weight	5g
Storage conditions	–40–85 °C

Note 1: Sensor measures molecules containing C-H bonds.

Disclaimer: Please refer to product specification for the complete technical details.

| | | |
Senseair
| | | |